



群頡科技企業股份有限公司 (C&C TEK CORP.)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712

[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)

e-mail : grace@cccoil.com.tw

| PART NUMBER | Inductance (uH) | L Test Frequency | DC Resistance () MAX. | Rated Current (A) MAX. |
|-------------|--------------------|---------------------|---------------------------|------------------------------|
| CC 105-3R3M | 3.3 | 5MHz | 0.030 | 5.84 |
| CC 105-4R7M | 4.7 | 5MHz | 0.035 | 4.50 |
| CC 105-5R6M | 5.6 | 5MHz | 0.040 | 3.88 |
| CC 105-6R0M | 6 | 5MHz | 0.050 | 3.64 |
| CC 105-100M | 10 | 2.52MHz | 0.060 | 2.60 |
| CC 105-120M | 12 | 2.52MHz | 0.070 | 2.45 |
| CC 105-150M | 15 | 2.52MHz | 0.080 | 2.27 |
| CC 105-180M | 18 | 2.52MHz | 0.090 | 2.15 |
| CC 105-220M | 22 | 2.52MHz | 0.100 | 1.95 |
| CC 105-270M | 27 | 2.52MHz | 0.110 | 1.76 |
| CC 105-330M | 33 | 2.52MHz | 0.120 | 1.50 |
| CC 105-390M | 39 | 2.52MHz | 0.140 | 1.37 |
| CC 105-470M | 47 | 2.52MHz | 0.170 | 1.28 |
| CC 105-560M | 56 | 2.52MHz | 0.190 | 1.17 |
| CC 105-680M | 68 | 2.52MHz | 0.220 | 1.11 |
| CC 105-820M | 82 | 2.52MHz | 0.250 | 1.00 |
| CC 105-101M | 100 | 1KHz | 0.350 | 0.97 |
| CC 105-121M | 120 | 1KHz | 0.400 | 0.89 |
| CC 105-151M | 150 | 1KHz | 0.470 | 0.78 |
| CC 105-181M | 180 | 1KHz | 0.630 | 0.72 |
| CC 105-221M | 220 | 1KHz | 0.730 | 0.66 |
| CC 105-271M | 270 | 1KHz | 0.970 | 0.57 |
| CC 105-331M | 330 | 1KHz | 1.150 | 0.52 |
| CC 105-391M | 390 | 1KHz | 1.300 | 0.48 |
| CC 105-471M | 470 | 1KHz | 1.480 | 0.42 |
| CC 105-561M | 560 | 1KHz | 1.900 | 0.33 |
| CC 105-681M | 680 | 1KHz | 2.250 | 0.28 |
| CC 105-821M | 820 | 1KHz | 2.550 | 0.24 |