



群韻科技企業股份有限公司 (C&C TEK CORP .)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)
e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (nH) at 100MHz	Inductance Tolerance	Q Typical		SRF (MHz) MIN.	DC Resistance (Ω) MAX.	Rated Current (mA)
			100 MHz	800 MHz			
CMF 160808-1N2S	1.2	S	13	60	>6000	0.1	300
CMF 160808-1N5S	1.5	S	13	47	>6000	0.1	300
CMF 160808-1N8S	1.8	S	12	51	>6000	0.12	300
CMF 160808-2N2S	2.2	S	12	38	>6000	0.16	300
CMF 160808-2N7S	2.7	S	12	38	>6000	0.2	300
CMF 160808-3N3	3.3	S, K	12	41	5700	0.22	300
CMF 160808-3N9	3.9	S, K	13	50	5600	0.25	300
CMF 160808-4N7	4.7	S, K	12	41	4800	0.28	300
CMF 160808-5N6	5.6	S, K	12	42	4350	0.29	300
CMF 160808-6N8	6.8	J, K	12	40	3750	0.3	300
CMF 160808-8N2	8.2	J, K	13	34	3300	0.33	300
CMF 160808-10N	10	J, K	13	45	2850	0.35	300
CMF 160808-12N	12	J, K	15	46	2700	0.4	300
CMF 160808-15N	15	J, K	15	48	2400	0.45	300
CMF 160808-18N	18	J, K	16	48	2050	0.5	300
CMF 160808-22N	22	J, K	17	45	1850	0.55	300
CMF 160808-27N	27	J, K	17	43	1750	0.6	300
CMF 160808-33N	33	J, K	18	39	1500	0.65	300
CMF 160808-39N	39	J, K	17	37	1350	0.7	300
CMF 160808-47N	47	J, K	17	35	1200	0.9	300
CMF 160808-56N	56	J, K	17	32	1100	1	300
CMF 160808-68N	68	J, K	18	34	1000	1.5	300
CMF 160808-82N	82	J, K	18	32	900	1.8	300
CMF 160808-R10	100	J, K	15	16	830	2.1	300

: Inductance tolerance (J : ± 5%, K : ± 10%, S : ± 3 nH)