



群韻科技企業股份有限公司 (C&C TEK CORP.)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)
e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (uH)	L Test Frequency	DC Resistance () MAX.	Rated Current (A) MAX.
CC 43-1R0M	1.0	7.96MHz	0.049	2.56
CC 43-1R2M	1.2	7.96MHz	0.055	2.54
CC 43-1R4M	1.4	7.96MHz	0.057	2.52
CC 43-1R8M	1.8	7.96MHz	0.064	1.95
CC 43-2R2M	2.2	7.96MHz	0.072	1.75
CC 43-2R7M	2.7	7.96MHz	0.079	1.58
CC 43-3R3M	3.3	7.96MHz	0.087	1.44
CC 43-3R9M	3.9	7.96MHz	0.094	1.33
CC 43-4R7M	4.7	7.96MHz	0.109	1.15
CC 43-5R6M	5.6	7.96MHz	0.126	0.99
CC 43-6R8M	6.8	7.96MHz	0.132	0.95
CC 43-8R2M	8.2	7.96MHz	0.147	0.84
CC 43-100M	10	2.52MHz	0.182	0.80
CC 43-120M	12	2.52MHz	0.210	0.78
CC 43-150M	15	2.52MHz	0.235	0.76
CC 43-180M	18	2.52MHz	0.280	0.74
CC 43-220M	22	2.52MHz	0.378	0.68
CC 43-270M	27	2.52MHz	0.522	0.62
CC 43-330M	33	2.52MHz	0.540	0.56
CC 43-390M	39	2.52MHz	0.587	0.52
CC 43-470M	47	2.52MHz	0.844	0.44
CC 43-560M	56	2.52MHz	0.937	0.42
CC 43-680M	68	2.52MHz	1.117	0.37
CC 43-820M	82	2.52MHz	1.170	0.35
CC 43-101M	100	1KHz	1.200	0.32
CC 43-151M	150	1KHz	1.560	0.25
CC 43-181M	180	1KHz	2.200	0.23
CC 43-221M	220	1KHz	2.500	0.20
CC 43-331M	330	1KHz	4.050	0.18
CC 43-471M	470	1KHz	5.780	0.17
CC 43-561M	560	1KHz	7.100	0.16
CC 43-681M	680	1KHz	8.030	0.15
CC 43-102M	1000	1KHz	10.700	0.14