



群頡科技企業股份有限公司 (C&C TEK CORP.)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712

[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)

e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (uH)	L Test Frequency	DC Resistance () MAX.	Rated Current (A) MAX.
CC 54-1R0M	1.0	7.96MHz	0.025	4.00
CC 54-1R2M	1.2	7.96MHz	0.027	3.90
CC 54-2R2M	2.2	7.96MHz	0.035	3.50
CC 54-2R4M	2.4	7.96MHz	0.040	3.30
CC 54-3R3M	3.3	7.96MHz	0.045	3.00
CC 54-3R9M	3.9	7.96MHz	0.050	2.70
CC 54-4R7M	4.7	7.96MHz	0.054	2.50
CC 54-5R2M	5.2	7.96MHz	0.055	2.40
CC 54-5R6M	5.6	7.96MHz	0.065	2.20
CC 54-6R8M	6.8	7.96MHz	0.070	2.00
CC 54-8R2M	8.2	7.96MHz	0.075	1.56
CC 54-100M	10	2.52MHz	0.100	1.44
CC 54-120M	12	2.52MHz	0.120	1.40
CC 54-150M	15	2.52MHz	0.140	1.30
CC 54-180M	18	2.52MHz	0.150	1.23
CC 54-220M	22	2.52MHz	0.180	1.11
CC 54-270M	27	2.52MHz	0.200	0.97
CC 54-300M	30	2.52MHz	0.220	0.92
CC 54-330M	33	2.52MHz	0.230	0.88
CC 54-390M	39	2.52MHz	0.320	0.80
CC 54-470M	47	2.52MHz	0.370	0.72
CC 54-560M	56	2.52MHz	0.420	0.68
CC 54-680M	68	2.52MHz	0.460	0.61
CC 54-820M	82	2.52MHz	0.600	0.58
CC 54-101M	100	1KHz	0.700	0.52
CC 54-121M	120	1KHz	0.930	0.48
CC 54-151M	150	1KHz	1.100	0.40
CC 54-181M	180	1KHz	1.380	0.38
CC 54-221M	220	1KHz	1.570	0.35
CC 54-331M	330	1KHz	1.750	0.30
CC 54-681M	680	1KHz	4.500	0.25
CC 54-102M	1000	1KHz	6.500	0.20