



群韻科技企業股份有限公司 (C&C TEK CORP .)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)
e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (uH)	L Test Frequency	DC Resistance () MAX.	Rated Current (A) MAX.
CCB 0603-3R0M	3.0	1KHz	0.0250	2.00
CCB 0603-4R7M	4.7	1KHz	0.0284	1.60
CCB 0603-6R8M	6.8	1KHz	0.0354	1.50
CCB 0603-100M	10	1KHz	0.0532	1.30
CCB 0603-150M	15	1KHz	0.0745	1.00
CCB 0603-220M	22	1KHz	0.1040	0.77
CCB 0603-330M	33	1KHz	0.1480	0.69
CCB 0603-470M	47	1KHz	0.2100	0.59
CCB 0603-680M	68	1KHz	0.2900	0.50
CCB 0603-101M	100	1KHz	0.4300	0.42