



**群頡科技企業股份有限公司 (C&C TEK CORP.)**

10F., No.236-1, Jhongsing Rd.,  
Sijhih City, Taipei County 221, Taiwan  
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712

[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)

e-mail : [grace@cccoil.com.tw](mailto:grace@cccoil.com.tw)

PART NUMBER	Inductance (uH)	L Test Frequency	DC Resistance ( ) MAX.	Rated Current (A) MAX.
CCB 1004-100M	10	1KHz	0.0384	2.50
CCB 1004-150M	15	1KHz	0.0472	2.20
CCB 1004-220M	22	1KHz	0.0591	1.90
CCB 1004-330M	33	1KHz	0.0815	1.60
CCB 1004-470M	47	1KHz	0.1000	1.40
CCB 1004-680M	68	1KHz	0.1400	1.20
CCB 1004-101M	100	1KHz	0.2000	1.00
CCB 1004-151M	150	1KHz	0.3500	0.79
CCB 1004-221M	220	1KHz	0.4700	0.65
CCB 1004-331M	330	1KHz	0.6800	0.54
CCB 1004-471M	470	1KHz	1.0300	0.47
CCB 1004-681M	680	1KHz	1.5000	0.38
CCB 1004-102M	1000	1KHz	2.8000	0.29
CCB 1004-152M	1500	1KHz	3.4000	0.22