



群頡科技企業股份有限公司 (C&C TEK CORP .)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)
e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (μ H)	Q MIN.	L,Q Test Frequency (MHz)	Self-Resonant Frequency (MHz) MIN.	Dc Resistance () MAX.	Rated Current (mA) MAX.
CML 201212-2R7K	2.7 \pm 10%	45	10	45	0.75	30
CML 201212-3R3K	3.3 \pm 10%	45	10	41	0.8	30
CML 201212-3R9K	3.9 \pm 10%	45	10	38	0.9	30
CML 201212-4R7K	4.7 \pm 10%	45	10	35	1	30
CML 201212-5R6K	5.6 \pm 10%	50	4	32	0.9	15
CML 201212-6R8K	6.8 \pm 10%	50	4	29	1	15
CML 201212-8R2K	8.2 \pm 10%	50	4	26	1.1	15
CML 201212-100K	10 \pm 10%	50	2	24	1.15	15
CML 201212-120K	12 \pm 10%	50	2	22	1.25	15