



**群頡科技企業股份有限公司 (C&C TEK CORP.)**

10F., No.236-1, Jhongsing Rd.,  
Sijhih City, Taipei County 221, Taiwan  
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712  
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)  
e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (uH)	L Test Frequency	DC Resistance ( ) MAX.	Rated Current (A) MAX.
CC 52-2R2M	2.2	2.52MHz	0.050	2.50
CC 52-3R3M	3.3	2.52MHz	0.088	2.40
CC 52-3R5M	3.5	2.52MHz	0.092	2.30
CC 52-4R3M	4.3	2.52MHz	0.120	2.20
CC 52-4R7M	4.7	2.52MHz	0.130	2.10
CC 52-6R8M	6.8	2.52MHz	0.166	1.70
CC 52-100M	10	2.52MHz	0.223	1.35
CC 52-120M	12	2.52MHz	0.285	1.10
CC 52-150M	15	2.52MHz	0.335	0.90
CC 52-220M	22	2.52MHz	0.499	0.75
CC 52-270M	27	2.52MHz	0.564	0.62
CC 52-330M	33	2.52MHz	0.659	0.56
CC 52-390M	39	2.52MHz	0.790	0.52
CC 52-470M	47	2.52MHz	0.920	0.48
CC 52-680M	68	2.52MHz	1.264	0.37
CC 52-820M	82	2.52MHz	1.469	0.27
CC 52-101M	100	1KHz	1.697	0.20
CC 52-121M	120	1KHz	2.280	0.19
CC 52-151M	150	1KHz	2.912	0.17
CC 52-181M	180	1KHz	3.800	0.16
CC 52-221M	220	1KHz	4.706	0.15
CC 52-331M	330	1KHz	7.306	0.13
CC 52-471M	470	1KHz	9.282	0.12
CC 52-681M	680	1KHz	14.040	0.10