



**群頡科技企業股份有限公司 (C&C TEK CORP .)**

10F., No.236-1, Jhongsing Rd.,  
Sijhih City, Taipei County 221, Taiwan  
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712  
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)  
e-mail : [grace@cccoil.com.tw](mailto:grace@cccoil.com.tw)

PART NUMBER	Inductance (uH)	L Test Frequency	DC Resistance ( ) MAX.	Rated Current (A) MAX.
CCD 8D28-2R5N	2.5	100KHz	0.0156	4.50
CCD 8D28-3R3N	3.3	100KHz	0.0182	4.00
CCD 8D28-4R7N	4.7	100KHz	0.0247	3.40
CCD 8D28-7R3N	7.3	100KHz	0.0390	2.80
CCD 8D28-100N	10	100KHz	0.0470	2.50
CCD 8D28-150N	15	100KHz	0.0690	1.90
CCD 8D28-220N	22	100KHz	0.0990	1.60
CCD 8D28-330N	33	100KHz	0.1560	1.30
CCD 8D28-470N	47	100KHz	0.1950	1.15
CCD 8D28-680N	68	100KHz	0.2860	0.92
CCD 8D28-101N	100	100KHz	0.4300	0.75