



群韻科技企業股份有限公司 (C&C TEK CORP .)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)
e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (nH) at 100MHz	Inductance Tolerance	Q Typical		SRF (MHz) MIN.	DC Resistance (Ω) MAX.	Rated Current (mA)
			100 MHz	800 MHz			
CMF 100505-1N0S	1	S	10	28	13500	0.1	300
CMF 100505-1N2S	1.2	S	9	28	12000	0.1	300
CMF 100505-1N5S	1.5	S	10	30	10500	0.1	300
CMF 100505-1N8S	1.8	S	10	28	9400	0.1	300
CMF 100505-2N2S	2.2	S	10	30	8700	0.2	300
CMF 100505-2N7S	2.7	S	10	30	7700	0.2	300
CMF 100505-3N3	3.3	S, K	10	30	6800	0.3	300
CMF 100505-3N9	3.9	S, K	11	31	6300	0.3	300
CMF 100505-4N7	4.7	S, K	10	30	5700	0.4	300
CMF 100505-5N6	5.6	S, K	11	31	5100	0.4	300
CMF 100505-6N8	6.8	J, K	10	31	4550	0.5	300
CMF 100505-8N2	8.2	J, K	12	34	4100	0.5	300
CMF 100505-10N	10	J, K	12	32	3750	0.6	300
CMF 100505-12N	12	J, K	12	31	2950	0.6	300
CMF 100505-15N	15	J, K	11	30	2600	0.7	300
CMF 100505-18N	18	J,K	11	29	2350	0.8	300
CMF 100505-22N	22	J,K	11	28	1950	0.9	300
CMF 100505-27N	27	J,K	12	27	1750	1	300
CMF 100505-33N	33	J,K	10	25	1700	1.5	200
CMF 100505-39N	39	J, K	10	25	1650	1.8	200
CMF 100505-47N	47	J, K	9	23	1300	2	200

: Inductance tolerance (J : $\pm 5\%$, K : $\pm 10\%$, S : ± 3 nH)