



群韻科技企業股份有限公司 (C&C TEK CORP.)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)
e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (nH) at 100MHz	Inductance Tolerance	Q Typical		SRF (MHz) MIN.	DC Resistance () MAX.	Rated Current (mA)
			100 MHz	800 MHz			
CMF 201212-R12	120	J, K	19		650	1.3	250
CMF 201212-R15	150	J, K	20		550	1.5	250
CMF 201212-R18	180	J, K	20		500	1.8	250
CMF 201212-R22	220	J, K	20		450	2	200
CMF 201212-R27	270	J, K	20		400	2.5	200
CMF 201212-R33	330	J, K	20		380	3	150
CMF 201212-R39	390	J, K	20		330	3.5	150
CMF 201212-R47	470	J, K	19		300	4	100

: Inductance tolerance (J : $\pm 5\%$, K : $\pm 10\%$)