



群頡科技企業股份有限公司 (C&C TEK CORP.)

10F., No.236-1, Jhongsing Rd.,
Sijhih City, Taipei County 221, Taiwan
TEL: 886-2-2695-8710 FAX: 886-2-2695-8712
[Http://www.cccoil.com.tw](http://www.cccoil.com.tw)
e-mail : grace@cccoil.com.tw

PART NUMBER	Inductance (μ H)	Q MIN.	L,Q Test Frequency (MHz)	Self-Resonant Frequency (MHz) MIN.	Dc Resistance () MAX.	Rated Current (mA) MAX.
CML 321611-47NM	0.047 \pm 20%	20	50	320	0.15	300
CML 321611-68NM	0.068 \pm 20%	20	50	280	0.25	300
CML 321611-R10K	0.10 \pm 10%	20	25	235	0.25	250
CML 321611-R12K	0.12 \pm 10%	20	25	220	0.3	250
CML 321611-R15K	0.15 \pm 10%	20	25	200	0.3	250
CML 321611-R18K	0.18 \pm 10%	20	25	185	0.4	250
CML 321611-R22K	0.22 \pm 10%	20	25	170	0.4	250
CML 321611-R27K	0.27 \pm 10%	20	25	150	0.5	250
CML 321611-R33K	0.33 \pm 10%	20	25	145	0.6	250
CML 321611-R39K	0.39 \pm 10%	25	25	135	0.5	200
CML 321611-R47K	0.47 \pm 10%	25	25	125	0.6	200
CML 321611-R56K	0.56 \pm 10%	25	25	115	0.7	150
CML 321611-R68K	0.68 \pm 10%	25	25	105	0.8	150
CML 321611-R82K	0.82 \pm 10%	25	25	100	0.9	150
CML 321611-1R0K	1.0 \pm 10%	45	10	75	0.4	100
CML 321611-1R2K	1.2 \pm 10%	45	10	65	0.5	100
CML 321611-1R5K	1.5 \pm 10%	45	10	60	0.5	50
CML 321611-1R8K	1.8 \pm 10%	45	10	55	0.5	50
CML 321611-2R2K	2.2 \pm 10%	45	10	50	0.6	50
CML 321611-2R7K	2.7 \pm 10%	45	10	45	0.6	50
CML 321611-3R3K	3.3 \pm 10%	45	10	41	0.7	50
CML 321611-3R9K	3.9 \pm 10%	45	10	38	0.8	50
CML 321611-4R7K	4.7 \pm 10%	45	10	35	0.9	50
CML 321611-5R6K	5.6 \pm 10%	50	4	32	0.7	25
CML 321611-6R8K	6.8 \pm 10%	50	4	29	0.8	25
CML 321611-8R2K	8.2 \pm 10%	50	4	26	0.9	25
CML 321611-100K	10 \pm 10%	50	2	24	1	25
CML 321611-120K	12 \pm 10%	50	2	22	1.05	15